

Zeta Addressable Securetone 2 Sounder

(ZAS2/R, ZAS2/W)



The Securetone 2 addressable sounder has a low profile design which makes it ideal for locations where sounders are required to be unobtrusive. It is designed to work with the complete range of Zeta addressable control panels.

The sounder is supplied configured to its maximum volume. However there is a potentiometer which may be used to adjust the sound level if required.

An 8 way DIP switch is used to set the address, where switch 8 is the shadow operative switch. When in the position ON, the sounder will behave normally. When in the OFF position, the sounder will listen to commands without answering to the panel. This allows multiple sounders to be configured at the same address to allow for synchronised sounder operation.

Features

- ✓ Complies fully to EN-54 part 3
- ✓ 85 dB @ 1 metre
- ✓ Low current consumption
- ✓ Loop isolation option
- ✓ Compatible with all Zeta addressable panels
- ✓ DIP switch address setting
- ✓ ?Shadow sounder ability?

Model	ZAS2/R	ZAS2/W
Part No.	42-520	42-521
Sound Output	85 dB @ 1 metre	
Alarm Tone	Intermittent Tone - 800-970Hz (0.5s each) Pulsed Tone - 970Hz (0.5s on, 0.5s off)	
Maximum Sounders Per Loop	64	
Short Circuit Isolator	No	
Operating Voltage	17-30V DC	
Quiescent Current	0.9 mA	
Alarm Current	5.5 mA	
Maximum Cable Size	2.5mm ²	
Operating Temperature	0 °C to 40 °C	
Maximum Humidity	95% RH Non Condensing	
IP Protection Rating	IP43	
Material	Red ABS Plastic	White ABS Plastic
Size, Diameter x Height	100mm x 37.5mm	
Weight	120g	